

Power Density Spectrum - Continuous Time

Young W Lim

January 22, 2021

Copyright (c) 2018 Young W. Lim. Permission is granted to copy, distribute and/or modify this document under the terms of the GNU Free Documentation License, Version 1.2 or any later version published by the Free Software Foundation; with no Invariant Sections, no Front-Cover Texts, and no Back-Cover Texts. A copy of the license is included in the section entitled "GNU Free Documentation License".

This work is licensed under a Creative Commons "Attribution-NonCommercial-ShareAlike 3.0 Unported" license.



Based on
Probability, Random Variables and Random Signal Principles,
P.Z. Peebles,Jr. and B. Shi

Energy and average power in time domain

for continuous time signals

Energy, Average Power – in time domain

a deterministic signal $x(t)$

$$x_T(t) = \begin{cases} x(t) & -T < t < T \\ 0 & \text{otherwise} \end{cases}$$

the energy

$$E(T) = \int_{-T}^{+T} x^2(t) dt$$

the average power

$$P(T) = \frac{1}{2T} \int_{-T}^{+T} x^2(t) dt$$

Fourier transform

for continuous time signals

Fourier Transform Pair $x(t) \iff X(\omega)$

Fourier transform

$$X(\omega) = \int_{-\infty}^{\infty} x(t) e^{-j\omega t} dt$$

a deterministic signal $x(t)$

$$x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(\omega) e^{j\omega t} d\omega$$

Fourier transform of $x_T(t)$

for continuous time signals

bounded duration, bounded variation

for a finite T , $x_T(t)$ is assumed to have bounded variation

$$\int_{-T}^{+T} |x(t)| dt < \infty$$

the Fourier transform of $x_T(t)$

$$\begin{aligned} X_T(\omega) &= \int_{-\infty}^{+\infty} x_T(t) e^{-j\omega t} dt \\ &= \int_{-T}^{+T} x(t) e^{-j\omega t} dt \end{aligned}$$

Fourier transforms of $x_T(t)$ and $X_T(t)$

for continuous time signals

deterministic $X_T(\omega)$ v.s. random $X_T(\omega)$

a **deterministic** sample signal $x_T(t)$

$$x_T(t) \iff X_T(\omega)$$

a **random process** signal $X_T(t)$

$$X_T(t) \iff X_T(\omega)$$

Parseval's theorem (I)

for continuous time signals

for a deterministic $x_T(t)$

a **deterministic** sample signal $x_T(t)$

$$\int_{-\infty}^{+\infty} x_T(\tau)x_T^*(\tau)d\tau = \frac{1}{2\pi} \int_{-\infty}^{+\infty} X_T(\omega)X_T^*(\omega)d\omega$$

$$\int_{-\infty}^{+\infty} |x_T(\tau)|^2 d\tau = \frac{1}{2\pi} \int_{-\infty}^{+\infty} |X_T(\omega)|^2 d\omega$$

Parseval's theorem (II)

for continuous time signals

for a deterministic $x_T(t)$ v.s. a random $X_T(t)$

- a **deterministic** signal $x_T(t) \iff X_T(\omega)$

$$\int_{-T}^{+T} |x_T(t)|^2 dt = \frac{1}{2\pi} \int_{-\infty}^{+\infty} |X_T(\omega)|^2 d\omega$$

- a **random** signal $X_T(t) \iff X_T(\omega)$

$$\int_{-T}^{+T} E \left[|X_T(t)|^2 \right] dt = \frac{1}{2\pi} \int_{-\infty}^{+\infty} E \left[|X_T(\omega)|^2 \right] d\omega$$

Energy and average power in frequency domain for continuous time signals

Energy, Average Power – Parseval's theorem applied

a deterministic signal $x_T(t)$

$$x_T(t) = \begin{cases} x(t) & -T < t < T \\ 0 & \text{otherwise} \end{cases}$$

the **energy** by Parseval's theorem

$$E(T) = \int_{-T}^{+T} x^2(t) dt = \frac{1}{2\pi} \int_{-\infty}^{+\infty} |X_T(\omega)|^2 d\omega$$

the **average power** by Parseval's theorem

$$P(T) = \frac{1}{2T} \int_{-T}^{+T} x^2(t) dt = \frac{1}{2\pi} \int_{-\infty}^{+\infty} \frac{|X_T(\omega)|^2}{2T} d\omega$$

$E(T)$ and $P(T)$ in frequency domain – deterministic case for continuous time signals

deterministic $x_T(t) \iff X_T(\omega)$

the **energy** for the **deterministic** $X_T(\omega)$

$$E(T) = \frac{1}{2\pi} \int_{-\infty}^{+\infty} |X_T(\omega)|^2 d\omega$$

the **average power** for the **deterministic** $X_T(\omega)$

$$P(T) = \frac{1}{2\pi} \int_{-\infty}^{+\infty} \frac{|X_T(\omega)|^2}{2T} d\omega$$

the **power density spectrum** for the **deterministic** $X_T(\omega)$

$$\lim_{T \rightarrow \infty} \frac{|X_T(\omega)|^2}{2T}$$

$E(T)$ and $P(T)$ in frequency domain – random case for continuous time signals

random $X_T(t) \iff X_T(\omega)$

the **energy** for the **random** $X_T(\omega)$

$$E(T) = \frac{1}{2\pi} \int_{-\infty}^{+\infty} E[|X_T(\omega)|^2] d\omega$$

the **average power** for the **random** $X_T(\omega)$

$$P(T) = \frac{1}{2\pi} \int_{-\infty}^{+\infty} \frac{E[|X_T(\omega)|^2]}{2T} d\omega$$

the **power density spectrum** for the **random** $X_T(\omega)$

$$\lim_{T \rightarrow \infty} \frac{E[|X_T(\omega)|^2]}{2T}$$

Average power $P(T)$ – bounded duration $(-T, +T)$ for continuous time signals

$$P(T) = \frac{1}{2T} \int_{-T}^{+T} x^2(t) dt$$

- not the average power in a **random process**
only the power in **one** sample function
 - to obtain the **average power** over all possible realizations,
replace $x(t)$ by $X(t)$
take the **expected value** of $x^2(t)$, that is $E[X^2(t)]$
 - then, the **average power** is a **random variable**
with respect to the **random process** $X(t)$
- not the average power in an **entire** sample function
 - take $T \rightarrow \infty$ to include all power in the **ensemble** member

Average power P_{XX} – unbounded duration $(-\infty, +\infty)$ for continuous time signals

$$P(T) = \frac{1}{2T} \int_{-T}^{+T} x^2(t) dt$$

- replace $x(t)$ by the **random variable** $X(t)$
- take the **expected value** of $x^2(t)$, that is $E[X^2(t)]$

$$P(T) = \frac{1}{2T} \int_{-T}^{+T} E[X^2(t)] dt$$

- take $T \rightarrow \infty$ to include all power

$$P_{XX} = \lim_{T \rightarrow \infty} P(T) = \lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^{+T} E[X^2(t)] dt$$

Average power P_{XX} – time average $A[\bullet]$

for continuous time signals

The time average

$$A_T[\bullet] = \frac{1}{2T} \int_{-T}^T [\bullet] dt \quad A[\bullet] = \lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^T [\bullet] dt$$

time average and sample average operations

$$\boxed{P_{XX} = \lim_{T \rightarrow \infty} P(T)} = \lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^{+T} E[X^2(t)] dt$$
$$= A[E[X^2(t)]]$$

Measuring average power

for continuous time signals

for deterministic and random signals

the **average power** $P(T)$ for a deterministic signal $x(t)$

$$P(T) = \frac{1}{2T} \int_{-T}^{+T} x^2(t) dt$$

the **average power** P_{XX} for a random process $X(t)$

$$\begin{aligned} P_{XX} &= \lim_{T \rightarrow \infty} P(T) \\ &= \lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^{+T} E[X^2(t)] dt \\ &= A[E[X^2(t)]] \end{aligned}$$

Power density spectrum $S_{XX}(\omega)$

for continuous time signals

the average power via power density

the average power P_{XX} for the random process $X_T(\omega)$

$$\begin{aligned} P_{XX} &= \frac{1}{2\pi} \int_{-\infty}^{+\infty} \boxed{\lim_{T \rightarrow \infty} \frac{E[|X_T(\omega)|^2]}{2T}} d\omega \\ &= \frac{1}{2\pi} \int_{-\infty}^{+\infty} \boxed{S_{XX}(\omega)} d\omega \end{aligned}$$

the power density spectrum $S_{XX}(\omega)$

$$\boxed{S_{XX}(\omega)} = \boxed{\lim_{T \rightarrow \infty} \frac{E[|X_T(\omega)|^2]}{2T}}$$

Properties of Power Spectrum

for continuous time signals

- $S_{XX}(\omega) \geq 0$
- $S_{XX}(-\omega) = S_{XX}(\omega)$ $X(t)$ real
- $S_{XX}(\omega)$ real
- $\frac{1}{2\pi} \int_{-\infty}^{+\infty} S_{XX}(\omega) d\omega = A [E [X^2(t)]]$
- $S_{\dot{X}\dot{X}}(\omega) = \omega^2 S_{XX}(\omega)$
- $\frac{1}{2\pi} \int_{-\infty}^{+\infty} S_{XX}(\omega) e^{j\omega t} d\omega = A [R_{XX}(t, t + \tau)]$
- $S_{XX}(\omega) = \int_{-\infty}^{+\infty} A [R_{XX}(t, t + \tau)] e^{-j\omega\tau} d\tau$

Equations involving $S_{XX}(\omega)$

for continuous time signals

Definition

the average power related equation

$$\frac{1}{2\pi} \int_{-\infty}^{+\infty} S_{XX}(\omega) d\omega = A [E [X^2(t)]]$$

the autocorrelation related equation

$$\frac{1}{2\pi} \int_{-\infty}^{+\infty} S_{XX}(\omega) e^{j\omega t} d\omega = A [R_{XX}(t, t + \tau)]$$

Average power related equation

for continuous time signals

Definition

the average power related equation

$$\frac{1}{2\pi} \int_{-\infty}^{+\infty} S_{XX}(\omega) d\omega = A [E [X^2(t)]]$$

- a random process $X(t)$ in time domain
- a random process $X_T(\omega)$ in frequency domain

Average power P_{XX} in time / frequency domain

for continuous time signals

Definition

Using a random process $X(t)$ in time domain

$$P_{XX} = \lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^{+T} E[X^2(t)] dt$$
$$= \boxed{A[E[X^2(t)]]}$$

Using a random process $X_T(\omega)$ in frequency domain

$$P_{XX} = \frac{1}{2\pi} \int_{-\infty}^{+\infty} \boxed{\lim_{T \rightarrow \infty} \frac{E[|X_T(\omega)|^2]}{2T}} d\omega$$
$$= \frac{1}{2\pi} \int_{-\infty}^{+\infty} \boxed{S_{XX}(\omega)} d\omega$$

Autocorrelation related equation

for continuous time signals

Definition

the average power related equation

$$\frac{1}{2\pi} \int_{-\infty}^{+\infty} S_{XX}(\omega) e^{j\omega t} d\omega = A[R_{XX}(t, t + \tau)]$$

- auto-correlation function

$$R_{XX}(t, t + \tau) = E[X(t)X(t + \tau)] \Rightarrow R_{XX}(\tau)$$

- a random process $X(t)$ in time domain
- a random process $X_T(\omega)$ in frequency domain

Fourier transforms of autocorrelation functions for continuous time signals

Definition

Fourier transform of an autocorrelation functions

$$S_{XX}(\omega) = \int_{-\infty}^{+\infty} R_{XX}(\tau) e^{-j\omega\tau} d\tau$$

$$S_{\dot{X}\dot{X}}(\omega) = \int_{-\infty}^{+\infty} R_{\dot{X}\dot{X}}(\tau) e^{-j\omega\tau} d\tau$$

- auto-correlation function

$$R_{XX}(t, t + \tau) = E[X(t)X(t + \tau)] \Rightarrow R_{XX}(\tau)$$

$$R_{\dot{X}\dot{X}}(t, t + \tau) = E[\dot{X}(t)\dot{X}(t + \tau)] \Rightarrow R_{\dot{X}\dot{X}}(\tau)$$

- a random process $X(t)$ in time domain
- $\dot{X}(t) = \frac{d}{dt}X(t)$: the derivative of $X(t)$

Fourier transform of a derivative function for continuous time signals

Definition

Fourier transform of an autocorrelation functions

$$x(t) \iff X(\omega)$$
$$\frac{d^n}{dt^n} x(t) \iff (j\omega)^n X(\omega)$$

Power Density Spectrum and Auto-correlation

for continuous time signals

Definition

$$S_{XX}(\omega) = \int_{-\infty}^{+\infty} A[R_{XX}(t, t + \tau)] e^{-j\omega\tau} d\tau$$
$$\frac{1}{2\pi} \int_{-\infty}^{+\infty} S_{XX}(\omega) e^{j\omega t} d\omega = A[R_{XX}(t, t + \tau)]$$

for a WSS $X(t)$, $A[R_{XX}(t, t + \tau)] = R_{XX}(\tau)$

$$S_{XX}(\omega) = \int_{-\infty}^{+\infty} R_{XX}(\tau) e^{-j\omega\tau} d\tau$$
$$R_{XX}(\tau) = \frac{1}{2\pi} \int_{-\infty}^{+\infty} S_{XX}(\omega) e^{+j\omega\tau} d\omega$$

Power Spectrum and Auto-Correlation Functions

for continuous time signals

Definition

the power spectrum

$$S_{XX}(\omega) = \int_{-\infty}^{+\infty} R_{XX}(\tau) e^{-j\omega\tau} d\tau$$

the auto-correlation function

$$R_{XX}(\tau) = \frac{1}{2\pi} \int_{-\infty}^{+\infty} S_{XX}(\omega) e^{+j\omega\tau} d\omega$$

RMS Bandwidth

for continuous time signals

Definition

the standard deviation is
a measure of the spread in a density function.
the analogous quantity for the normalized power spectrum is
a measure of its spread that we call the rms bandwidth
(root-mean-square)

$$W_{rms}^2 = \frac{\int_{-\infty}^{+\infty} \omega^2 S_{XX}(\omega) d\omega}{\int_{-\infty}^{+\infty} S_{XX}(\omega) d\omega}$$

RMS Bandwidth and Mean Frequency

for continuous time signals

Definition

the mean frequency $\bar{\omega}_0$

$$\bar{\omega}_0 = \frac{\int_{-\infty}^{+\infty} \omega S_{XX}(\omega) d\omega}{\int_{-\infty}^{+\infty} S_{XX}(\omega) d\omega}$$

the rms bandwidth

$$W_{rms}^2 = \frac{4 \int_{-\infty}^{+\infty} (\omega - \bar{\omega}_0)^2 S_{XX}(\omega) d\omega}{\int_{-\infty}^{+\infty} S_{XX}(\omega) d\omega}$$

