

Power Density Spectrum - Continuous Time

Young W Lim

October 3, 2019

Copyright (c) 2018 Young W. Lim. Permission is granted to copy, distribute and/or modify this document under the terms of the GNU Free Documentation License, Version 1.2 or any later version published by the Free Software Foundation; with no Invariant Sections, no Front-Cover Texts, and no Back-Cover Texts. A copy of the license is included in the section entitled "GNU Free Documentation License".

This work is licensed under a Creative Commons "Attribution-NonCommercial-ShareAlike 3.0 Unported" license.



Based on
Probability, Random Variables and Random Signal Principles,
P.Z. Peebles,Jr. and B. Shi

Fourier Transform

N Gaussian random variables

Definition

$$X(\omega) = \int_{-\infty}^{\infty} x(t) e^{-j\omega t} dt$$

$$x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(\omega) e^{j\omega t} d\omega$$

Average Power

N Gaussian random variables

Definition

$$x_T(t) = \begin{cases} x(t) & -T < t < T \\ 0 & \text{otherwise} \end{cases}$$

$$E(T) = \int_{-T}^{+T} x^2(t) dt$$

$$P(T) = \frac{1}{2T} \int_{-T}^{+T} x^2(t) dt$$

